THE SILICON DRIFT DETECTOR AND ITS USE IN A VERTEX TRACKER

APPROVED BY
DISSERTATION COMMITTEE:

Supervisor: ______________________

____

____

____

____

For Martha Lane Orr, who waited

and

For Annemarie Roth, who understood

THE SILICON DRIFT DETECTOR AND ITS USE IN A VERTEX TRACKER

by

DAVID M. READ, B.S.

DISSERTATION

Presented to the Faculty of the Graduate School of

The University of Texas at Austin

in Partial Fulfillment

of the Requirements

for the Degree of

DOCTOR OF PHILOSOPHY

THE UNIVERSITY OF TEXAS AT AUSTIN

May 1996

Acknowledgements

The assistance and guidance of Dr. G. W. Hoffmann is gratefully acknowledged. The generous help of Drs. K. Wilson and C. Pruneau in resolving software difficulties is also acknowledged. Finally, the patient explanations and helpful suggestions of Dr. R. L. Ray are appreciated.

THE SILICON DRIFT DETECTOR
AND ITS USE IN A VERTEX TRACKER

Publication No. ____________________

David M. Read, Ph.D.
The University of Texas at Austin, 1996

Supervisor: G.W. Hoffmann

Silicon Drift Detectors (SDDs) represent a step forward in the detection of fast charged particles in heavy-ion experiments. They exhibit excellent spatial and charge resolution, and tolerate high occupancies and event rates. The design of silicon drift detectors is discussed, prototype detectors are tested, computer code to simulate the performance and analysis of data is developed, and a working detector composed of SDDs is discussed and simulated.

Table of Contents

Acknowledgements **v**

Abstract **vi**

List of Tables **x**

List of Figures **xi**

Chapter 1. STAR physics with an SVT **1**

1.1 STAR goals 1

1.2 Physics Capabilities of the Silicon Vertex Tracker (SVT) 4

1.2.1 Flavor physics 4

1.2.2 Low $p_\perp$ physics 10

1.2.3 HBT Interferometry with the SVT 13

1.2.4 Other SVT capabilities which enhance the physics performance of the STAR baseline detector 15

Chapter 2. Principles and design of the Silicon Drift Detector **31**

2.1 Principles of operation 31

2.1.1 Introduction 31

2.1.2 Silicon drift detectors as a p-n-p junction 34

Chapter 3. Testing SDDs in a particle beam **47**

3.1 The experimental setup 47

3.1.1 Overview 47

3.1.2 Readout and data acquisition 48

3.2 Data analysis software 54

3.2.1 Overview 54

3.2.2 Detailed description of the routines in SCAT 55

3.3 Results from the analysis of test run data 59

3.3.1 Signal characteristics 59
3.3.2 Determining the position of a hit from the cluster charge distribution 67
3.3.3 Detector efficiency 70
3.3.4 Charge reconstruction 73
3.3.5 Position resolution 77

Chapter 4. Detector simulations and data analysis code 81
4.1 Simulating the silicon drift detector 81
4.2 Analyzing silicon drift detector data 83
4.2.1 The SAD package 84
4.2.2 The SAS package 86
4.2.3 The SCL package 87
4.2.4 The SCS package 93
4.2.4.1 Processing isolated hits 93
4.2.4.2 Processing merged hits 94
4.3 Simulations of detector performance 98
4.3.1 Detector efficiency 102
4.3.2 Detector occupancy 106
4.3.3 Position resolution 109
4.3.4 Charge resolution 116
4.3.5 The effects of the 10-bit to 8-bit mapping table 122

Chapter 5. SDDs in a Vertex Tracker 127
5.1 Overview of the Silicon Vertex Tracker 127
5.2 Simulations of SVT Performance 129
5.2.1 SVT Tracking Efficiency 130
5.2.2 SVT Momentum Resolution 131

Appendix A. Derivation of formulae for extracting parameters of a Gaussian distribution from few data points 137
A.1 Formulae for two data points 137
A.2 Formulae for three data points 138

Bibliography 141

Vita **145**

List of Tables

3.1 Table of cluster anode counts in SDD 395 69

4.1 Efficiency and Purity at 400 e^- noise 107
4.2 Efficiency and Purity at 800 e^- noise 108
4.3 SVT detector occupancies by layer 109

5.1 Specifications of the Silicon Vertex Tracker 129

List of Figures

1.1 Secondary track reconstruction efficiency for the SVT alone . . . 5

1.2 Armenteros plot showing K_s^0 and Λ separation based on SVT information . . . 6

1.3 Invariant mass spectra of reconstructed Λ particles based on SVT and TPC tracking information. . . . 8

1.4 Invariant mass spectra of reconstructed Ξ particles based on SVT and TPC tracking information. . . . 9

1.5 The effect of Bose Einstein condensation and n-body symmetrization on the π spectrum. . . . 11

1.6 Momentum resolution for π reconstructed in the SVT alone . . 12

1.7 Measurements of correlation function C(Q_{out}) from K_s^0 pair reconstruction with SVT and TPC . . . 16

1.8 Measurements of correlation function C(Q_{side}) from K_s^0 pair reconstruction with SVT and TPC . . . 17

1.9 Primary track reconstruction efficiency for SVT and TPC as a function of momentum . . . 18

1.10 Classification of tracks in the SVT as a function of momentum based on the tracking efficiency . . . 19

1.11 dE/dx vs. momentum for several particle species in STAR . . . 21

1.12 Energy loss in a small range of particle momentum . . . 22

1.13 SVT performance in areas related to HBT measurements . . . 24

1.14 Impact parameter resolution from the SVT and TPC . . . 26

1.15 High $p_\perp$ resolution from the TPC alone and the SVT+TPC system 27

1.16 Main vertex resolution measured by the SVT and TPC as a function of system size . . . 29

1.17 Pion momentum distribution and mean for different mechanisms on an event by event basis . . . 30

2.1 Cross-sectional schematic view of a silicon drift detector . . . 34

2.2 P-N junctions and depletion layers . . . 36

2.3 The silicon drift detector interpreted as a partially or fully depleted p-n-p junction . . . 42

2.4 Map of the electric potential in a silicon drift detector 45

3.1 Schematic view of the SVT test run experimental setup 48
3.2 Schematic overview of the test run data acquisition system . . . 50
3.3 A single hit displayed by *Pad Monitor* 60
3.4 Sample output from the *Plothits* visualization program 61
3.5 Occupancy of SDD 395 in the test beam 63
3.6 Occupancy of SDD 405 in the test beam 65
3.7 Occupancy of SDD 416 in the test beam 66
3.8 Histogram of number of anodes in a cluster 68
3.9 Drift and transverse cluster widths vs. drift distance 71
3.10 Cluster charge vs. drift distance 74
3.11 Peak height vs. drift distance 75
3.12 Total cluster charge 76
3.13 Transverse residues from good tracking events 78
3.14 Drift residues from good tracking events 79

4.1 Logic flow in the `svt_medium` routine 85
4.2 Two conditions for adjacent sequences to be considered to be overlapping 90
4.3 Three examples of possiblities for merged-hit cluster shapes . . . 92
4.4 Distribution of cluster 2nd moments 96
4.5 Uncorrected errors in drift-direction positions 99
4.6 Fitting the drift-position errors 100
4.7 Errors in drift position after correction 101
4.8 Efficiency and purity of the analysis process as a function of threshold settings 105
4.9 Errors in the reconstructed hit position at various drift distances 111
4.10 Drift position resolution as a function of drift distance and threshold levels 112
4.11 Transverse position resolution as a function of drift distance and threshold levels 113
4.12 Drift position resolution as a function of drift distance and noise levels 114

4.13 Transverse position resolution as a function of drift distance and noise levels 115
4.14 Charge reconstruction efficiency at 400 e^- noise 117
4.15 Improved charge reconstruction efficiency at 400 e^- noise 119
4.16 Charge reconstruction efficiency vs. noise levels 121
4.17 An alternate method of reconstructing the total deposited charge in a cluster 123
4.18 Position resolution with a linear 10-bit to 8-bit mapping table . 125
4.19 Charge reconstruction with a linear 10-bit to 8-bit mapping table 126

5.1 Schematic layout of the SVT 128
5.2 Momentum resolution in the SVT at 400 e^- noise 132
5.3 Momentum resolution in the SVT at 800 e^- noise 133

Chapter 1

STAR physics with an SVT

The material in this chapter has appeared previously [1].

1.1 STAR goals

The primary physics goal of the RHIC project is to collide heavy nuclei with sufficient energy to produce a transition from hot, dense, hadronic matter to a color de-confined, chirally symmetric plasma of quarks and gluons (QGP). STAR will focus mainly on the investigation of soft processes resulting in hadron production at central rapidities and transverse momenta below 2 GeV/c but, in addition, will study hard QCD processes such as the production of jets, mini-jets and hard photons. STAR will also investigate nucleon structure functions and effects of quark and gluon shadowing through proton-proton and proton-nucleus interactions. The intent of the experimental program is to measure many observables, some of which are obtained on an event-by-event basis, and study their dependence on the size of the colliding system, the collision impact parameter and total energy.

The time evolution of nucleus-nucleus collisions is thought to involve an initial parton scattering, pre-equilibrium stage, an intermediate thermalization stage in which the QGP might be formed, and a final expansion and hadronization stage. Observables can be associated with each stage which convey different information about the collision dynamics. For example, hard parton scatterings in the initial pre-equilibrium stage result in high $p_\perp$ particles, jets, high energy γs, and charmed mesons. Conditions during the intermediate thermalization stage (*i.e.,* hot hadronic gas or QGP) affect the production of mini-jets, strangeness, anti-baryons, isospin anomalies and energy/entropy fluctuations. Multi-strange baryon and ϕ meson production are strongly dependent on strangeness density during this stage and are therefore sensitive indicators of possible chiral symmetry restoration in the QGP. Global properties such as size and temperature during the final hadronization stage can be determined by the $p_\perp$ spectra and by $\pi\pi$ and KK HBT interferometry.

The baseline configuration of the STAR detector consists of a large room temperature solenoidal magnet, a time projection chamber (TPC) for charged particle tracking, and trigger counters (vertex position detectors, central trigger barrel). Charged particle momenta will be measured with the TPC at mid-rapidity ($|\eta| \leq 2$) with full azimuthal coverage and a transverse momentum, $p_\perp$, threshold of about 150 MeV/c. Particle identification through measurement of ionization density (dE/dx) will be accomplished for particles emitted with $|\eta| \leq 2$ and $150 \leq p_\perp \leq 600$MeV/c. With the TPC alone, STAR is limited to the study of hadron production with $p_\perp$ above 150 MeV/c and has a modest efficiency and accuracy for the study of short lived particles decaying before they reach the inner layer of the TPC. Multi-strange baryons and anti-baryons cannot be studied with the STAR baseline detector.

The purpose of the STAR Silicon Vertex Tracker (SVT) upgrade is to provide unique capabilities for the measurement of several of the preceding list of observables as well as to enhance the overall performance of STAR. Unique capabilities of the SVT include the detection of multi-strange baryons (Ξ^- and Ω^-) and measurement of low $p_\perp$ ($40 \leq p_\perp \leq 200$ MeV/c) spectra. Measurements of rare particles such as the D mesons and strange composite objects, which are impossible to observe with the TPC alone, might become accessible with the SVT. The SVT will provide substantial improvement in the momentum resolution for high $p_\perp$ particles, in the reconstruction efficiency for short lived neutral particles such as K_s^0, ϕ, Λ, and $\overline{\Lambda}$, and in two-track resolution for HBT studies owing to the excellent position resolution achievable with Si drift chamber technology. The SVT will also enhance track reconstruction and particle identification for soft charged particles such as $\pi^\pm$, $K^\pm$, p, $\overline{p}$, d and $\overline{d}$, will enable better determination of the primary vertex, and will help distinguish particles resulting from secondary decays.

It is unlikely that conclusive evidence of QGP formation at RHIC can be based on a single observable or signature; instead we will require the simultaneous observation of many signatures. It is expected that only a consistent analysis of many signals coming from all stages of the collision may lead to an unambiguous identification of the phase transition. STAR complemented with the SVT represents a powerful instrument for studying this possible transition to a new state of matter.

A detailed description of the integrated STAR system (baseline detector plus upgrades) can be found in the original STAR conceptual design report (CDR) [2].

In this document, we outline a proposal for the construction of an SVT for STAR which uniquely addresses low-$p_\perp$ and flavor physics otherwise unsatisfactorily covered by other RHIC detectors.

1.2 Physics Capabilities of the Silicon Vertex Tracker (SVT)

The SVT detector will enhance STAR capabilities for particle identification and momentum resolution and will extend the detector acceptance for low $p_\perp$ phenomena. It will offer unique capabilities for the study of strange and multi-strange particle production and in addition will allow HBT interferometry studies using neutral particles. The SVT will also expand the STAR third level trigger capabilities. These topics are discussed in more detail in the following.

1.2.1 Flavor physics

The different stages of nucleus-nucleus collisions (parton scattering, thermalization, expansion and hadronization) will be studied by measuring the yield and spectral distribution of produced hadrons. The formation of a QGP might be revealed through an enhancement of the relative abundance of strange to non-strange quarks [3]. Considerable reduction of the ratio of strange to anti-strange baryon production is also expected with the formation of a QGP [4]. Measurements of multiply strange baryon ratios (*e.g.* Ξ^-/Λ) are very sensitive to enhanced strange quark density [5], [6] which might result from chiral symmetry restoration in the QGP. The addition of the SVT with its high position resolution close to the production vertex allows the elimination of most of the combinatoric background and drastically improves the detection efficiency for strange particles. Figure 1.1 shows the tracking efficiency for secondary tracks in the SVT alone as a function of momentum.

To illustrate the positive impact of the excellent SVT position resolution we show in fig. 1.2 an Armenteros scatter plot for K_s^0 and Λ reconstructed from combined SVT and TPC tracks. Although no particle identification information is used in this plot, a clean separation of K_s^0 and Λ is obtained.



Figure 1.1: Secondary track reconstruction efficiency for the SVT alone

The capability of the combined SVT and TPC detector for reconstructing strange and multistrange particles is indicated by the invariant mass spec-



Figure 1.2: Armenteros plot showing K_s^0 and Λ separation based on SVT information

tra in figures 1.3 and 1.4 (see also [7]). To obtain the Λ spectrum a complete tracking algorithm in the SVT was employed, including momentum information from the TPC, matching efficiency, and detector resolution factors derived from simulations. The decay particles are identifiable via energy loss in the combined tracking system. The Ξ spectrum assumes ideal tracking. Based on the simulation for the Λ, we expect a modest reduction of the signal to noise ratio for the Ξ in the case of realistic tracking.

The ability of the SVT+TPC system to reconstruct multi-strange baryons coupled with the ability of STAR to study global event observables makes the proposed detector system unique among the RHIC experiments.

Modification of the mass and decay widths of certain very short lived particles has been predicted to occur in extremely dense hadronic matter and might also signal the formation of a QGP and chiral symmetry restoration [8]. Because of its narrow width and simple decay schemes the ϕ meson has received particular attention [9]. The excellent momentum resolution and wide $p_\perp$ coverage of combined SVT and TPC detectors will allow the study of possible medium modifications of the ϕ meson mass and width through the $K^+ + K^-$ decay channel.

Charm and in particular open charm production is currently believed to be an excellent indicator of the initial parton scattering stage of heavy ion collisions [10]. Because such particles must propagate through the medium they might also be sensitive to the production of the QGP. As the D-meson production cross section (σ_c/σ_s) and lifetime ($c\tau \approx 200\ \mu$m) are small and considering that most D decay channels are complex, the detection capability of open charm with STAR SVT and TPC is unclear at present. Strong enhancements in the

D meson production, predicted recently [11], will produce a cleaner signal than that expected from previous estimates of the production cross section. It is apparent however that such a measurement cannot be achieved without the excellent position resolution afforded by the SVT [12].



Figure 1.3: Invariant mass spectra of reconstructed Λ particles based on SVT and TPC tracking information.



Figure 1.4: Invariant mass spectra of reconstructed Ξ particles based on SVT and TPC tracking information.

1.2.2 Low $p_\perp$ physics

Enhancements in the low momentum part of invariant cross section spectra were discovered in heavy ion reactions at CERN and AGS. Although several explanations were suggested by theorists, the phenomena related to pion $p_\perp$ spectra under 200 MeV/c is not fully understood [13], [14], [15], [16]. First results from the AGS for low $p_\perp$ kaons also reveal a very steep component at very low $p_\perp$ (below 50 MeV/c) which might be linked to a QGP phenomenon [17]. If these enhancements persist at the higher incident RHIC energies and in the baryon free rapidity region studied with STAR, explanations based on resonance models [18] could be excluded in favor of more exotic models based on some form of phase transition [16]. The high position resolution and low $p_\perp$ acceptance of the SVT for pions, kaons and protons is mandatory for such studies at RHIC. Several collective effects have been hypothesized which predict changes (enhancements) in the low $p_\perp$ particle spectra as well as correlations among the low $p_\perp$ particles. 'Van Hove bubbles' [18], localized plasma formation, might lead to spatially correlated hadronization of low $p_\perp$ particles and can be verified by measuring fluctuations of the yield in rapidity. Chiral condensate models [16] predict enhancements in the low $p_\perp$ particle spectra; disoriented chiral condensate models [19] in addition predict anomalous ratios of charged to neutral pions on an event-by-event basis. Hints of this behavior may have been observed in cosmic ray collisions [20]. Information on the yield of low $p_\perp$ charged pions on an event-by-event basis, as well as their correlation behavior as a function of centrality may provide information about the hadronization of a chiral condensate [21]. Bose-Einstein condensation [22] of pions is predicted to occur if a critical pion density can be reached at RHIC energies. If so, the majority of the pions will be emitted with very low momenta. In the case of coherent emission the mean momentum depends only on the source radius. SVT capabilities for detecting Bose-Einstein condensation effects in the RHIC environment are detailed in [23]. Figure 1.5 shows the magnitude of the effect.



Figure 1.5: The effect of Bose Einstein condensation and n-body symmetrization on the π spectrum.



Figure 1.6: Momentum resolution for π reconstructed in the SVT alone

Figure 1.6 shows the pion momentum resolution for reconstructed tracks between 60 MeV/c and 250 MeV/c. The open dots represent the improvement achievable by including de/dx information from the SVT in the calculation. Although moderate, the resolution in fig. 3b is sufficient to permit momentum reconstruction, which preserves the shape of the spectrum at low $p_\perp$. The presence of a low $p_\perp$ enhancement will not only be determined for a large ensemble of events but, given the charged pion multiplicities expected at RHIC, it is statistically feasible to measure a shift in the mean of the momentum spectrum, event-by-event, which could be used as an exotic third level trigger (see section 1.2.4).

1.2.3 HBT Interferometry with the SVT

Measurements of two particle Bose-Einstein correlations can be interpreted in terms of the space-time structure of the emitting source (HBT interferometry) and may provide a signature of QGP formation [24], [25]. Theoretical studies show that kaon interferometry offers significant advantages over pions with respect to final state interactions and resonance formation, which obscure the interpretation of the data [26], [27]. Also, studies of interferometry based on hydrodynamic models [28] reveal that in order to best determine the structure of the emitting system the two-particle spectrum should include a wide range of the total two particle momenta including very low momenta. We discuss two applications of HBT interferometry for STAR in which the SVT makes a vital contribution: (1) by extending the acceptance to low $p_\perp$ and (2) by enabling neutral kaon (K_s^0) interferometry.

Increasing the $p_\perp$ acceptance improves the two pion statistics and might enable STAR to perform $\pi-\pi$ HBT on an event-by-event basis. Also, the study of two-particle correlations over an extended range of two-particle mean $p_\perp$ will provide better constraints on collision dynamics.

Neutral kaon interferometry via the SVT is unique to STAR. Central Au+Au collisions produce on the order of 200 short lived neutral kaons per event and of these approximately 10% are expected to be reconstructed using SVT tracking of the decay pions. The K_s^0 correlation function offers an obvious advantage due to the absence of Coulomb effects. A comparison between the results from charged and neutral kaon HBT will quantitatively determine the Coulomb effect. K_s^0 HBT is also not affected by two-track resolution, which is a limiting factor in charged particle correlations. K_s^0 are identified by their decay into charged pions. These pions are emitted back-to-back along a line oriented randomly in the K_s^0 rest frame. Even for two K_s^0 at exactly zero relative momentum the decay pions are well separated in configuration and momentum space and can be measured with the same efficiency as if the relative momentum of the kaons was large. Moreover, because the K_s^0 is not a strangeness eigenstate, the K_s^0-K_s^0 correlation includes a unique interference term that provides additional space-time information [29] as well as insight into possible strangeness distillation effects [30] in cases where the source baryon density is appreciable.

We simulated the K_s^0 HBT performance of STAR with the SVT for central Au+Au HIJING events including an imposed Bose-Einstein correlation enhancement as expected from a 10 fm radius spherical source. Considering that the kaons can be expected to freeze out earlier than the pions, this radius is plausible. The event reconstruction was simplified by assuming perfect matching between SVT and TPC tracks. Tracking inefficiencies and detector resolution were taken into account however. Details of the procedure can be found in [31]. Figures 1.7 and 1.8 show the correlation functions C(Q_{out}) and C(Q_{side}) [24], [25]. Q_{out}, which refers to the relative transverse momentum along the direction of the average pair momentum is predicted to offer the best discrimination between plasma and hadron gas scenarios [25], [32]. Our simulation suggests that with the SVT a measurement of Q_{out} from K_s^0 HBT is achievable. The SVT is essential for K_s^0 interferometry, because of its tracking capability which enables efficient secondary vertex reconstruction.

1.2.4 Other SVT capabilities which enhance the physics performance of the STAR baseline detector

The SVT will further enhance the capabilities of the STAR baseline detector in areas where the TPC performance is improved by combining SVT and TPC information. For the simulations presented in this section, full tracking within the SVT and matching with TPC tracks were performed as in the analysis of real events, unless otherwise mentioned.

Primary track reconstruction: The SVT not only extends the range of primary particle reconstruction in STAR to lower momenta, but also enhances the tracking efficiency for momenta below 400 MeV/c compared to the TPC alone. Figure 1.9 shows the primary track reconstruction efficiency for SVT and TPC as a function of the momentum. The plot corresponds to the present level of tracking capabilities. Improvements in both tracking software packages are expected in the future. Figure ref:track-eff shows the number of ghost tracks in the SVT tracking as a function of momentum. This number is greatly reduced by matching tracks between SVT and TPC.



Figure 1.7: Measurements of correlation function C(Q_{out}) from K_s^0 pair reconstruction with SVT and TPC



Figure 1.8: Measurements of correlation function C(Q_{side}) from K_s^0 pair reconstruction with SVT and TPC



Figure 1.9: Primary track reconstruction efficiency for SVT and TPC as a function of momentum



Figure 1.10: Classification of tracks in the SVT as a function of momentum based on the tracking efficiency

Particle Identification: The good de/dx resolution of the SVT will complement significantly the particle identification capabilities of the TPC. Figure 1.11 shows the average energy loss as a function of $p_\perp$ for the combined SVT+TPC system. Figure 1.12 shows a slice in momentum space. The addition of the SVT extends the upper limit for $K-\pi$ separation to about 600 MeV/c and for $p-\pi$ to about 800 MeV/c. The improvement in particle identification will aid in HBT analysis, strangeness production studies, and in overall event characterization.



Figure 1.11: dE/dx vs. momentum for several particle species in STAR



Figure 1.12: Energy loss in a small range of particle momentum

Two-track resolution: HBT analysis depends strongly on the ability to separate tracks that have small relative momenta. We show in fig. 1.13(a) the result of a laboratory measurement of the minimum relative distance needed for two hit separation on a Silicon Drift Chamber as a function of the size of the signal [33] . The SVT also contributes to enhance the pion pair statistics on an event by event basis, by extending the momentum range for reconstruction of pion tracks. Figure 1.13(b) shows the uncertainty of the RMS radius as a function of two track separation and lower momentum cutoff. The dashed curves correspond to the TPC separation range projected back to the outer SVT radius, the solid curve reflects the SVT separation power at the same point. The improved two track resolution of the SVT-TPC system will increase the maximum source size to which STAR is sensitive. Figure 1.13(c) shows that the SVT might enable HBT analysis on an event-by-event basis.

Secondary track reconstruction: The superior position resolution of the SVT enhances the identification and reconstruction of decay vertices, thus considerably reducing the combinatoric background to obtain a statistically significant sample of short lived particles such as ϕ, K_s^0 and Λ. This improvement results from the enhanced impact parameter resolution (see fig. 1.14). It is augmented by a constant SVT-TPC track matching efficiency of 86% in the momentum range from 200 MeV/c to 40 GeV/c. The high detection efficiency thus achieved will enable STAR to examine the correlation between the production cross section of these particles and other observables such as the total multiplicity, the transverse energy production of the particle's mean $p_\perp$ hence providing much more information than is available from inclusive distributions alone.



Figure 1.13: a.)Two hit separation as a function of signal width. b.) Uncertainty in rms radius for inclusive pion pair spectra as a function of lower momentum cutoff and two track separation at the outer radius of the SVT. Dashed curves reflect a range for the TPC performance depending on the drift gas, the solid curve is the result of the SVT analysis newline c.) Same as b.) for single event pion pair spectra.

High $p_\perp$: Momentum resolution for tracks with $p_\perp$ above 2 GeV/c is important for studies of gluon shadowing and jet quenching in the heavy-ion program as well as for some aspects of the pp spin physics program, in particular, the high momentum electron-hadron separation which is crucial for $W^\pm$ and Z^0 reconstruction and the study of Drell-Yan e^+e^- pairs. However, at high $p_\perp$ the momentum resolution of the TPC alone is seriously impaired by its modest position resolution ($\approx$ 700 μm), which limits the determination of the curvature of these nearly straight tracks. The addition of the SVT will provide vector information near the main vertex, greatly improving the momentum resolution for high $p_\perp$. Figure 1.15 shows the transverse momentum resolution as a function of $p_\perp$ for the TPC alone, and the TPC+SVT system. Note that at 50 GeV/c the improvement provided by the addition of the SVT is more than a factor of 5. Inclusion of the main vertex, as determined by the combined tracking system, will further improve the momentum resolution.

Primary vertex location: The SVT improves the main vertex position resolution and in turn augments primary particle momentum resolution, secondary particle identification, and high $p_\perp$ momentum resolution. A plot of primary vertex z resolution as a function of the mass of symmetric systems is shown in fig. 1.16 for the TPC and TPC+SVT systems. The addition of the SVT is of primary importance for the lighter systems. There is also a corresponding improvement in the two vertex separation from applying the Raleigh criteria to the results of the previous plot. This improved vertex resolution will be extremely useful in p-p collision studies at high luminosity where recorded events will include multiple primary vertices. It should also enhance STAR's ability to reject multi-vertex events when searching for events with rare multi-



Figure 1.14: Impact parameter resolution from the SVT and TPC



Figure 1.15: High $p_\perp$ resolution from the TPC alone and the SVT+TPC system

plicity fluctuations.

Trigger: The SVT will also provide third level trigger capabilities for STAR. Using existing algorithms, it should be feasible to achieve track reconstruction and particle identification via dE/dx with the SVT within a few tens of milliseconds. Thus, charged particle spectra are accessible on the third trigger level. Conditions could be envoked on e.g. particle ratio fluctuations and/or spectral shapes. One example of particular interest is the low momentum pion enhancement. Figure 1.17 shows the pion mean $p_{\perp}$ calculated event-by-event for 200 events for two different production mechanisms, as discussed in the previous chapter. The mean momentum is shifted by varying the chemical potential μ in the Boltzmann distribution. A μ near the pion mass corresponds to a condensation scenario in which the low momentum component of the spectrum is enhanced. Figure 1.17 shows the difference in the mean of the two spectra, which can be determined in time for a third level trigger decision.



Figure 1.16: Main vertex resolution measured by the SVT and TPC as a function of system size



Figure 1.17: Pion momentum distribution and mean for different mechanisms on an event by event basis

Chapter 2

Principles and design of the Silicon Drift Detector

2.1 Principles of operation

2.1.1 Introduction

Silicon Drift Detectors (SDDs) combine some of the best features of conventional gas drift chambers (such as the relatively small number of instrumented channels) with some of the best features of solid state detectors (such as excellent position and energy resolution).

Conventional gas drift chambers consist of thin high-voltage wires surrounded by a gas. When a fast charged particle passes through the gas, ion pairs are created; the electrons drift one direction in the field applied by the high-voltage wires, while the ions drift oppositely. The electrons are collected on the wires (anodes), and the resulting signal is amplified. The drift time of the electrons is measured, and a velocity map can be used to determine the drift distance from the drift time. These detectors have a relatively small number of instrumented channels, but their position resolution is often as large as 250 μm.

Solid state detectors, such as silicon microstrip detectors, work in a similar fashion. A thin wafer of n-type silicon with a continuous n^+n junction on one side has implanted, upon the other side, a series of very closely spaced p-type cathodes. A reverse-bias voltage is applied to deplete the bulk silicon and create a drift field. When a fast charged particle passes through the silicon, ion pairs are created. The electrons drift towards the n^+n junction, while the holes drift towards the p^+ cathodes.

Silicon microstrip detectors have excellent position resolution, due mostly to the fine cathode pitch (on the order of 25 μm) allowed by modern silicon processing techniques. However, since each cathode requires its own amplifier, the number of channels of amplifiers required can be quite large. For instance, for a modest microstrip detector, with 25 μm pitch, a 5-cm detector would require 2000 amplifiers. Additionally, this setup would yield only one-dimensional position information; a second layer of microstrip detector would be required to determine two-dimensional position.

Silicon drift detectors, in comparison, operate in a manner similar to convetional gas drift chambers, except that the drift gas is replaced by n-type silicon [34]. When the passage of fast charged particles ionizes a small region in the SDD, the resulting free electrons drift in the presence of an externally applied electric field, until they are collected at an anode. The drift velocity of the electrons in the silicon is given by

$$v_{drift} = \mu E \tag{2.1}$$

where v_{drift} is the drift velocity, μ is constant known as the *electron mobility*, and E is the local electric field. Since the mobility is a constant (unless the bulk silicon of the detector suffers from non-uniformities in the doping), a constant electric field implies a constant drift velocity. Thus, measuring the drift time allows calculation of the drift distance. Also, the charge cloud spreads as it drifts, due to diffusion and coulomb repulsion. This spreading causes signals to appear not only on the anode closest to the intersection point, but also on anodes adjacent to that central anode. By analyzing signals from several anodes, it is possible to determine a position transverse to the drift direction with substantially greater accuracy than the anode pitch.

Figure 2.1 shows a schematic side view of a silicon drift detector. In this detector, the electric field is generated by a series of cathodes which are held at successively decreasing (negative) potentials. This decreasing potential (a potential gradient) creates an electric field. The same potential is applied to each pair of cathodes across the thickness of the wafer, which is held at ground potential by the collection anode (see below). The effect of the cathodes is fully to deplete the bulk silicon, creating a conduction region. This conduction region is the region where the signal electrons drift.

At the end of the drift region, the collection anode is held at ground, while the cathode directly across the thickness of the wafer is held at a negative potential larger than its nearest neighbor cathode. This is done so that all of the electrons in a cloud are channeled to the collection anode with reasonable efficiency and minimal spreading of the charge cloud in the direction normal to the wafer.

By segmenting the collection anodes, a position transverse to the drift direction can be obtained. The position resolution of the SDD is comparable to that of a silicon microstrip detector, but the number of channels of amplification and readout is comparable to that of a gas drift chamber. For example, the SDDs designed for STAR have a 6 cm x 6 cm active area, with 240 anodes,



Figure 2.1: Cross-sectional schematic view of a silicon drift detector

spaced with 250 μm pitch. The position resolution of these devices is expected to be about 25 μm, which is similar to the resolution of the microstrip detector (although not quite as good), but much better than that of most gas drift chambers. However, the silicon drift detector requires much more time for the signal to drift to the anode (about 6 μs for a 3 cm drift in the STAR SDDs) than in silicon microstrip detectors. This means that the SDDs cannot be used for extremely high rate experiments.

2.1.2 Silicon drift detectors as a p-n-p junction

In order to understand how the cathodes deplete the bulk silicon and how this affects the operation of SDDs, it is useful to understand the physics of a p-n junction.

Figure 2.2 shows a schematic view of a p-n junction, after [36]. P-type silicon is produced by "doping" pure silicon with impurities of an element which has one less valence electron than silicon. Boron is the element usually chosen. N-type silicon contains impurities with one *more* valence electron than silicon (usually phosphorus). When contact is made between a sample of p-type silicon and a sample of n-type silicon, recombination of electrons from the n-type region with holes in the p-type region takes place. This recombination is possible because the electrons are thermally excited into the conduction band of the silicon, and become mobile.

Since both silicon samples were electrically neutral before being brought into contact, the result of this recombination is that the "extra" electrons from the n-type silicon end up on the 'p' side of the junction, leaving a net negative charge on the 'p' side and a net positive charge on the 'n' side. This local "space charge" creates a local electric field which eventually grows until further recombination of holes and electrons is energetically forbidden. The space charge region is known as the *depletion layer,* since all mobile charge carriers in the region have been removed, rendering it non-conductive. This has practical implications for the operation of the silicon drift detector, which will be discussed below.

N-type silicon is typically doped with a much lower impurity density than the p-type region; charge conservation then requires that the depletion layer extends farther into the n-type region than in the p-type region. This relationship can be quantified [35]:

$$N_a x_p = N_d x_n \tag{2.2}$$

where N_a is the density of acceptor impurities in the p-type region (in cm^{-3}),



Figure 2.2: P-N junctions and depletion layers

x_p is the extent of the depletion layer in the p-type region, N_d is the density of donor impurities in the n-type region, and x_n is the extent of the depletion layer in the n-type region.

We can calculate the local electric field described above. In the region far away from the junction, the p-type silicon will be charge-neutral. This can be written as

$$N_a - N_d + p - n = 0 \tag{2.3}$$

where p and n are the concentration of holes and free electrons, respectively.

Since $N_a >> N_d$ in the p-type region (essentially, one can consider N_d to be zero), and $n = 0$, we can identify

$$N_a = p \quad . \tag{2.4}$$

This is reasonable, considering that the ionization energy for the holes in the p-type region is a few tenths of an eV at most, while the band gap for silicon is roughly 1.12 eV. From this, one concludes that most of the holes (and free electrons) come from the impurities, rather than the intrinsic silicon.

Then we can write down an expression for the hole concentration

$$p = n_i e^{(E_i - E_F)/k_B T} \tag{2.5}$$

where E_i is the intrinsic energy of the silicon, E_F is the Fermi energy of the silicon, and n_i, the carrier (hole or electron) concentration of the silicon, is a tempera-ture-dependent density characteristic of the material. For room temperature (300 K) silicon, $n_i = 1.45 \times 10^{10}$ cm^{-3} . Finally, we can write down an expression [41] for the potential in the bulk p-type silicon relative to the Fermi level by combining equations 2.4 and 2.5:

$$\phi_p = -\frac{1}{q}(E_i - E_F) = -\frac{k_B T}{q} \ln \frac{N_a}{n_i} \quad . \tag{2.6}$$

Similarly, the potential in the n-type silicon, far from the junction, can be derived as

$$\phi_n = -\frac{1}{q}(E_i - E_F) = \frac{k_B T}{q} \ln \frac{N_d}{n_i} \quad . \tag{2.7}$$

Finally, we can solve for the so-called *built-in potential* Φ_{bi}:

$$\Phi_{bi} = \phi_n - \phi_p = \frac{k_B T}{q} \ln \frac{N_a N_d}{{n_i}^2} \quad . \tag{2.8}$$

For the silicon used in the STAR SDDs, the doping of the n-type bulk silicon is 1.0×10^{12} cm^{-3}, while the doping of the p-type field cathodes is 1.0×10^{18} cm^{-3}, yielding a built-in junction potential of approximately 0.58 V.

It is possible to calculate the depth of the depletion layer for a given junction. For this calculation, we will use the *abrupt junction* approximation, which considers the p-n junction to be infinitesimally thin; the silicon is doped only with donors when $x < 0$, and only with acceptors when $x > 0$.

First it is useful to note that the depth of the full depletion layer can be written as

$$W = x_p + x_n \quad . \tag{2.9}$$

In the depletion layer there is a space charge equal to the density of impurity ions (assuming that all impurities have been ionized). This, in turn, yields a differential equation for the electric potential (from Poisson's equation):

$$\frac{d^2\phi}{dx^2} = +q\frac{N_a}{\epsilon_{Si}} \qquad \text{for } -x_p \leq x < 0 \tag{2.10}$$

where ϵ_{Si} is the absolute dielectric constant in the silicon, approximately 1.05×10^{-14} F/cm. Similarly,

$$\frac{d^2\phi}{dx^2} = -q\frac{N_d}{\epsilon_{Si}} \qquad \text{for } 0 < x \leq x_n \ . \tag{2.11}$$

The electric field $\mathcal{E}$ can be obtained by integrating equations 2.10 and 2.11, yielding

$$\mathcal{E}(x) = -\frac{d\phi}{dx} = -\frac{qN_a}{\epsilon_{Si}}(x + x_p) \qquad \text{for } -x_p \leq x < 0 \tag{2.12}$$

and

$$\mathcal{E}(x) = -\frac{d\phi}{dx} = +\frac{qN_d}{\epsilon_{Si}}(x - x_n) \qquad \text{for } 0 < x \leq x_n \ . \tag{2.13}$$

Note that the maximum electric field is found at $x = 0$, where

$$\mathcal{E}_{max} = \frac{qN_a}{\epsilon_{Si}}x_p = \frac{qN_d}{\epsilon_{Si}}x_n \quad . \tag{2.14}$$

Integrating equations 2.12 and 2.13 yields the total potential difference from one side of the depletion layer to the other (namely the built-in potential Φ_{bi}) :

$$\begin{aligned}
\Phi_{bi} \quad &= -\int_{-x_p}^{x_n} \mathcal{E}(x)dx \\
&= -\int_{-x_p}^{0} \mathcal{E}(x)dx - \int_{0}^{-x_n} \mathcal{E}(x)dx \\
&= \frac{qN_a x_p^2}{2\epsilon_{Si}} + \frac{qN_d x_n^2}{2\epsilon_{Si}} \\
&= \frac{1}{2}\mathcal{E}_{max}W \quad .
\end{aligned} \tag{2.15}$$

Recalling the definition of $\mathcal{E}_{max}$, one can cast x_p and x_n in terms of $\mathcal{E}_{max}$:

$$x_p = \frac{\epsilon_{Si}}{q}\mathcal{E}_{max}\frac{1}{N_a} \tag{2.16}$$

and

$$x_n = \frac{\epsilon_{Si}}{q}\mathcal{E}_{max}\frac{1}{N_d} \quad . \tag{2.17}$$

Then we can rewrite equation 2.9 as

$$W = \frac{\epsilon_{Si}}{q}\mathcal{E}_{max}\left[\frac{1}{N_d} + \frac{1}{N_a}\right] \quad . \tag{2.18}$$

Thus

$$W = \frac{\epsilon_{Si}}{q}\mathcal{E}_{max}\left[\frac{N_a + N_d}{N_a N_d}\right] \tag{2.19}$$

and

$$\mathcal{E}_{max} = W\frac{q}{\epsilon_{Si}}\left[\frac{N_a N_d}{N_a + N_d}\right] \quad . \tag{2.20}$$

Inserting eq. 2.20 back into eq. 2.15 yields

$$\Phi_{bi} = W^2\frac{q}{2\epsilon_{Si}}\left[\frac{N_a N_d}{N_a + N_d}\right] \quad . \tag{2.21}$$

This lets us solve for the depletion depth W:

$$W = \sqrt{\frac{2\epsilon_{Si}}{q}\left[\frac{N_a + N_d}{N_a N_d}\right]\Phi_{bi}} \quad . \tag{2.22}$$

Using this formula for the STAR SDDs, with the values of N_a and N_d given earlier, the unbiased depletion layer has a depth of approximately 28 μm.

By applying a bias potential to the p-n junction, it is possible to allow electrons from the n-type region to reach the p-type region, thus increasing the depth of the depletion layer. When the bias potential is large enough, electrons are free to move anywhere within the silicon, and thus the depletion layer grows to include all of the silicon. In this state, the silicon is "fully depleted;" there are no free charge carriers available.

The depth of this layer can be calculated using an approximation to eq. 2.22. The first observation is that the p-type regions are doped much more heavily than the n-type region (see the values for N_a and N_d given earlier).

Also, we will be applying an external bias voltage, which will replace the Φ_{bi} term in eq. 2.22. Thus we arrive at an expression for the depth of the depletion layer in terms of the bias voltage V_{bias} and the doping density N_d:

$$W \simeq \sqrt{\frac{2\epsilon_{Si} V_{bias}}{qN_d}} \quad . \tag{2.23}$$

Thus the depth of the depletion layer is a constant times the square root of the bias voltage.

Silicon drift detectors can be considered to be two back-to-back p-n junctions. There is a depletion layer just underneath each p-type region (cathode), extending for some distance into the bulk silicon. Beyond this, the n-type silicon in the center of the wafer remains conducting. Conducting silicon can carry currents from thermal generation of electrons, which would show up as noise in the detector. Further, the conducting region would reduce the active area of the detector. Clearly it is desirable to deplete the entire thickness of the wafer, in order to reduce the volume of noise-generating silicon and increase the volume of active detector.

In order to do this, the bulk silicon is held at ground. Then identical negative potentials are applied to cathodes on either side of the silicon wafer. As the applied potential grows, the depletion layer also grows, until the silicon between the cathodes has become fully depleted. The potential in the bulk silicon can be calculated explicitly by integrating eq. 2.13, but clearly it has a quadratic dependence on the distance from the p-n junction interface.

Figure 2.3 shows a schematic view of a cross-section of silicon wafer, containing just one cathode pair. With no bias potential applied, small depletion layers form just beneath each cathode. The majority of the bulk silicon is



Figure 2.3: The silicon drift detector interpreted as a partially or fully depleted p-n-p junction

undepleted, leaving a conduction layer in the center of the wafer. If sufficient negative potential is applied to the cathodes, the depletion layer grows until the bulk silicon is fully depleted, leaving no conducting silicon except at the surface.

The "transport" electric field is applied as described earlier, by increasing the (negative) potential applied to the cathodes with distance from the anode.

In the case of the STAR SDDs, it is desirable to estimate the depth (in Volts) of the potential well in the depleted bulk silicon. We can start with eq. 2.23 and solve for V_{bias}, obtaining the maximum potential difference (between the field cathodes and the minimum potential in the bulk silicon):

$$\Delta V = \frac{qW^2}{2\epsilon_{Si}} N_d \quad . \tag{2.24}$$

To use this formula to calculate the potential difference, we must note that W in eq. 2.24 is one-half the thickness of the wafer (since we are modelling the SDD wafer as two back-to-back p-n junctions). It is also helpful to note that the expression shown is in the form of a constant times the doping density.

The design specification for the silicon used in the prototype STAR SDDs was $N_d = 1.0 \times 10^{-12}$ cm^{-3}, which would yield a potential "valley" with a depth of approximately 17.1 V. However, the silicon delivered from the manufacturor had a lower doping, of only $N_d \simeq 0.1 - 0.3 \times 10^{-12}$ cm^{-3}, which yielded a potential valley of at most 5.1 V. This left the bulk silicon only partially depleted, but there was an additional side effect. The potential minimum is in the center of the wafer thickness only if the field cathodes have identical applied potentials on each side of the wafer. The potential valley as designed was 17 V deep, which allowed for several volts of difference between facing cathodes. However, the delivered silicon, with its small potential valley (as little as 1.7 V!) required much more stringent control over the applied potentials than was possible. Small potential differences (as little as 2 V) between facing cathodes caused the electron cloud to drift to the surface of the silicon rather than the collection anode. As a result, the prototype STAR SDDs performed inadequately, with complete signal loss in some of the detectors. The next batch of silicon delivered by the vendor had a doping density within the specified limits, and the detectors performed as designed.

Figure 2.4 shows a 2-dimensional map of the electric potential over a small region close to the collection anode. This map was calculated by solving Poisson's equation (eqs. 2.10 and 2.11), given the known bulk quantities of the bulk silicon of the SDD wafers (dielectric constant, doping density, etc.) and knowing the boundary conditions (the applied potentials at the cathodes and the collection anode). For illustrative purposes, the quantity mapped is actually the negative of the electric potential.

The level, flat line segments along the near and far sides (0 and 275 μm depth) are the field cathodes. The large level line at 275 μm depth is the "focussing cathode." The gutter-like valley at 0 μm depth, between 950 μm and 1150 μm length is the collection anode. Over most of the cathodes the potential is identical on either side of the wafer; however, the 20 cathodes closest to the collection anode (the region pictured here) are biased with slightly unequal potentials so that the electron cloud will be "steered" towards the collection anode.

It is easy to see how the electron cloud from a charged-particle pas-



Figure 2.4: Map of the electric potential in a silicon drift detector

sage will drift "downhill" along the length of the detector, and then into the collection anode.

Chapter 3

Testing SDDs in a particle beam

In July, 1994, the STAR SVT collaboration used the B test beam area of the AGS at Brookhaven National Laboratory for in-beam studies of the operation and performance of prototype STAR-1 silicon drift detectors.

3.1 The experimental setup

3.1.1 Overview

The objective was to place a small number of SDDs in a particle beam of reasonably well-known composition in order to study signal and noise levels, detector efficiency, and position resolution. By placing three detectors in the beam, it is possible, in principle, to assemble hits in the detectors into tracks (which should be straight, since there was no strong magnetic field present in the experiment). These tracks can then be used to measure the distance between the track and each hit in the track; the resulting "residues" give a measure of the position resolution of the detectors.

Figure 3.1 shows a schematic layout of the experimental setup used during the SVT test run.

The AGS test beam contains several different particle species. Selection of particle charge and momentum is done via upstream bending magnets. An



Figure 3.1: Schematic view of the SVT test run experimental setup

inline Cerenkov counter can tag electrons. As a result, the SVT collaboration was able to select particles with negative charge, and then veto electrons with the Cerenkov counter. The remaining particles were almost all pions; tuning the upstream bending magnets allowed the collaboration to select momenta of interest. Similarly, it was possible to select protons in the beam by switching to a positive-charge setting for the magnets.

3.1.2 Readout and data acquisition

Figure 3.2 shows a schematic of the readout chain and the data acquisition system. The first element in the chain is the pre-amp board. The pre-amp boards reside on the carrier board which holds the SDD itself. The pre-amps are placed as close to the anodes of the SDD as possible in an effort to minimize the total noise in the system. From the pre-amp boards the signal is carried via a ribbon cable to a shaping amplifier. The shaping amps reside in an external box attached to the experimental apparatus. From the shaping amps, the signal is transferred to a readout board.

The readout board contains a switched capacitor array (SCA) and an analog to digital converter (ADC). The SCA is a device for taking "snapshots" of the incoming analog signal. It consists of a large number of small capacitors, and a transistor switch network which changes state in response to a clock signal. At each instant, the SCA connects the input signal to one of the capacitors. When the next clock cycle arrives, the switch changes so that the input signal is connected to the "next" capacitor in the array. In this fashion, the input signal is sampled at discrete times while the SCA cycles. The RC time constant of the capacitor is roughly 100 picoseconds, so the capacitor is fully charged (to the same potential as the input signal) after only 1 ns or so. Further, the gate to the capacitor is open for only a few ns after the start of the clock cycle. Thus the charge stored on the capacitor does not represent an instantaneous sample of the input signal, but rather something like a time-average of the input signal over the few ns that the charging gate is open. However, for signals which do not change greatly over the time that the gate is open, the SCA comes close to providing an instantaneous sample.

The main purpose of the SCA is to sample the incoming analog signal and hold it long enough for the ADC to digitize the signal. Since the ADC takes up to a microsecond to digitize each sample, some method of holding analog signals until the ADC can digitize them is required. The SCA fills this role.

In the test-run readout system, the SCA is started in response to an



Figure 3.2: Schematic overview of the test run data acquisition system

event trigger. It takes a fixed number of clock cycles to start (1.2 μs in our case). Further, the detector events are asynchronous with respect to the SCA clock, which means that the actual delay between the event and the start of the SCA is 1.2 μs plus a random interval which could be as much as one clock cycle (25 ns). Thus the DAQ system has a "dead time" of interval $1.2\mu s < t <= 1.225\mu s$. Since the detector itself is operational during this time, the charge cloud produced by the passage of the particle through the detector is drifting during the dead time. This translates to a "dead area" in the detector, positioned adjacent to the readout anode. The dead area stretched from the anode to a distance equal to the dead time multiplied by the drift velocity. For our experiment, the dead area was approximately 1.2 μs $\times$ 6 mm/μs= 7.2 mm in length. As described at the end of this section, the actual dead time was measured for each event, and the resulting position offsets were calculated.

In the final STAR system, the SCAs will cycle continuously, operating in a "ring buffer" mode. When the end of the capacitor array is reached, the SCA will simply start over, writing at the beginning of the array. When a "stop acquisition" signal arrives (in response to an event trigger), the SCA will stop "spinning," and await a "readout" signal. Thus the STAR SCAs will provide a backward-looking series of samples, with no dead time.

Once the ADC has digitized the samples stored in the SCA, the data is passed on to a receiver card. The link between the readout card and the receiver card is via an optical fiber. The receiver card is a VME module, residing in a VME crate. The receiver card stores the incoming data in a buffer, where the data await processing by a digital signal processor (DSP) chip, a Motorola DSP

56000. In principle, the DSP could be used to perform pedestal subtraction or other processing. In this case, however, the DSP simply copied the data from the buffer memory into global VME memory, visible to other devices on the VME bus.

Once the data is written to VME memory, it is available for reading by any device on the VME bus. In the test run experiment, a Motorola MVME-167 VME controller, an MC 68040-based computer running the VxWorks operating system, was used to buffer the event data in order that the events could be written to tape.

A buffer manager, based on OS-9 code developed for CERN experiment NA35, created a ring buffer which could store up to 10 events. Clients of the buffer manager call the manager and request to be added to a list of clients which should see "any" event, or "all events." Then registered clients can call the buffer manager and request to be served an event. The buffer manager keeps track of which events have been seen by which clients, and serves the proper event to each client which requests an event. Once an event has been "seen" by all clients who requested "every event" service, the event is released (i.e. marked so that it may be over-written by new events).

In the case of the SVT test run, the only clients served by the buffer manager were a "taper" client, which wrote events to 8mm tape, and the *"Pad Monitor"* program, which was developed as a diagnostic tool for visualizing individual events. Both of these clients operated remotely, from a Sun SPARCstation LX workstation. The workstation was connected to the VME controller by an ethernet cable, using TCP/IP as the network protocol. The 8mm tape drive was connected extenally to the workstation's SCSI bus.

The entire detector readout chain, from the PASA and SCA readout boards to the receiver cards, consisted of equipment designed and built for NA35. A limited number of PASA chips were available, so only 8 anodes of each of three detectors were instrumented. As a result, only one readout board was required to process the 24 resulting signals, and only one receiver card slot was used in the VME crate. Thus, the output from the experiment came packed into a single receiver board's output. The signals from each SDD were packed into one 128-anode output array, separated by many "dead" or "blank" channels.

The test-run DAQ system also included several scalers, ADCs and TDCs. The scalers were used to count total beam spills, event triggers, etc. The ADC modules were used to measure integrated charge from the beam scintillators, and the TDC modules were used to obtain timing information for trggering.

One TDC channel in particular was important; the start signal for it was the event trigger, while the stop signal came from the SCA clock. In other words, this TDC measured the random delay mentioned in the description of the dead time inherent in our SCA unit. By adding the random delay measured by the TDC to the known 1.2 μs delay in the SCA startup, it was possible to obtain a correct measurement for the total drift time of each hit in the SDDs. This is of obvious interest if one wishes to obtain the best position resolution possible, since the measured position of the hit is dependent on the drift time.

3.2 Data analysis software

3.2.1 Overview

The software written to analyze the test-run data was designed to mimic the way final STAR SVT software will operate. Some liberties were taken because many details of the operation of STAR software were not available at the time the test-run software was written.

The goal of the SVT Cluster-finder, Analyzer, and Tracker (SCAT) software was to take the output from the DAQ system and analyze it. This analysis consisted of performing pedestal subtraction, finding sequences in the raw data stream which are above threshold ("zero suppression"), assembling these sequences into clusters which represent a single particle crossing ("cluster-finding"), analyzing these clusters, and performing basic track-finding and analysis when possible.

SCAT operates in a very simple loop:

1. Get an event (from tape or from the buffer manager)

2. Check if the event was a pedestal event: if it is not a pedestal event and no pedestals have been encountered yet, loop back to position 1.

3. If it is a pedestal event, store the event in the pedestal buffer, and loop back to position 1.

4. Processing cannot reach this point unless the event is not a pedestal event (i.e. it's a "data" event), and a pedestal already exists in the buffer. Subtract the stored pedestal from the current event.

5. Unpack the event into structures for each detector. This is required because there are data from three detectors packed onto the readout board.

6. Loop over detectors:

7. Loop over the active anodes, calling the zero suppressor for each anode. The result from this stage is a table of HIT structures for each detector.

8. Call the cluster-finder to find clusters in the HIT table. This cluster-finder also analyzes the clusters for centroids, etc.

9. When all detectors have been processed, call the tracking routine, which finds tracks, fits them with straight lines, and calculates residues.

10. Write out required information and loop back to position 1.

3.2.2 Detailed description of the routines in SCAT

The zero suppressor developed for SCAT finds "sequences" of ADC values above a user-supplied threshold, and uses them to fill a HIT structure. The HIT structure contains information such as the detector and anode on which the sequence was located, the start and end times of the sequence, and a copy of the actual ADC values in the sequence. This differs somewhat from the information which will be present in the STAR software arrangement, but the principle is similar.

Sequences are located using a simple single-threshold algorithm. This algorithm requires that a certain number of consecutive ADC values be above threshold. In the case of the SVT test run, the requirement was that three

ADC values must be above a threshold of three ADC counts (this corresponds to 30 mV).

Once a sequence has been located, the information described above is copied into a HIT structure, and the process continues. The "start" and "end" values are numbers which represent the number of time buckets since the start of acquisition. The values copied into the HIT structure are not actually the beginning and end of the sequence, but the beginning minus two time buckets, and the end plus two time buckets. This allows for some rise and fall time in the peak, and perhaps some minor examination of the background around the peak.

Once the zero suppressor is finished, all HIT entries are converted to SUBHIT entries. The intent was to allow for de-convolution of merged hits (i.e. de-convolution of multiple peaks in a single sequence). However, the test-run setup all but eliminated the chance that there would be more than one hit in a detector per event, so no software was developed to deconvolute any merged hits. In principle, one HIT might produce several SUBHITs; in reality there was a one-to-one correspondence.

The SUBHIT structure contained fitted parameters rather than raw data. Routines were developed to fit the ADC values with a gaussian, extracting an amplitude, centroid and width for each sequence. Also, the SUBHIT structure contained the value of the sum of all ADC counts in the peak, to be used for dE/dx studies.

In all of the cluster analysis performed by SCAT, gaussian peak shapes were assumed. When fitting gaussians to digitized data, there are several distinct situations which can arise.

If only one data point is available, no fitting can be performed. In this case, the centroid associated with this single point must be merely the abscissa of the point itself.

If two data points are available, it is possible to write down an equation for the centroid of the gaussian which fits those two points, but only if a width of that gaussian is known a priori. The equations which gives the centroid and the uncertainty in the centroid two data points are given below, with the derivation in appendix A.

If three data points are present, then the width can be calculated directly, along with an uncertainty. Also derived in appendix A the equations for the width, centroid, and uncertainties are given here.

Finally, if four or more data points are available, the most accurate position measurement is obtained by fitting a gaussian to the data points by a chi-square minimization process. The code developed for use in SCAT uses Levenberg- Marquardt minimization methods, based on sample code contained in Numerical Recipes In C [42].

The first step in the analysis of HIT entries into SUBHIT entries was to fit a gaussian to the time-series data representing a hit on a single anode. Since the zero-suppressor required a minimum of three time buckets above threshold, the time-domain data always contained at least three time bins. Therefore the two-bin and one-bin cases never arose.

The SUBHIT structures were what was used by the cluster finder. The cluster finder tried to arrange SUBHITs into clusters. In principle, each cluster would represent one particle crossing in the detector. The cluster finder (a relatively simple one) decided if a SUBHIT belonged to a cluster if the centroids of the cluster and the candidate SUBHIT were within a small tolerance of each other.

Once the SUBHIT structures were organized into clusters, the individual clusters were analyzed as units to obtain a two-dimensional position. The drift-centroids were used to compute an overall drift position for the cluster; each SUBHIT centroid was weighted by the sum of all bins in the SUBHIT, and the resulting weighted-mean drift centroid was computed.

In the transverse (anode) direction, it was not always true that three or more samples were present. Primarily, hits close to the anode deposit charge on fewer anodes, but also small-amplitude hits do not contain enough charge to be above threshold on any but the central anode. As a result, the two-anode clusters become an important part of the analysis process; if they are discarded, a significant portion of the total data set is lost. See section 3.3.2 for details of how the two-anode clusters were processed.

Finally, the clusters on each detector are converted to space points. SCAT used generalized rotation and translation matrices (provided as input by the user) to convert positions on the wafer faces into three-dimensional coordinates in the laboratory frame. Once the clusters were converted to lab coordinates, a tracking algorithm tried to group sets of three clusters into tracks.

Once tracks were constructed, a least-squares fit to a line was constructed, giving a three-dimensional straight line for the track. Subsequently, each point of the track was used to calculate a residue (distance between point and where the track line crossed the detector on which the point was located) in drift- and anode-directions.

3.3 Results from the analysis of test run data

3.3.1 Signal characteristics

The first thing done when analyzing the test-run data was to look at the signals from the detector with the *"Pad Monitor"* program. *Pad Monitor* shows a 2-dimensional overview of the data from a receiver card, coding the signal strength by color.

Pad Monitor also has the ability to show a single anode's data as a time series, with zoom capability. Figure 3.3 shows a pulse from a typical event. In this figure, the ADC pedestal has been shifted to allow the digitized signal to include negative analog values; the shifted pedestal is 20 ADC counts less than the normal pedestal. Hence, the zero-voltage level appears at 20 ADC counts in this plot.

Once average pulse characteristics were identified, it was possible to set the threshold and minimum length for the zero suppressor. The values selected were 3 ADC counts (30 mv) and 3 time buckets.

After setting the threshold and minimum length, SCAT was used to make a pass through all data tapes, writing only the zero-suppressed data to disk. This allowed for high-speed re-analysis of the data when bugs in SCAT were corrected or when new clustering or tracking algorithms were being tested. Since the SCSI tape drive used had a maximum transfer rate of 250 kB/sec, and events were 64 kB in size, the maximum processing rate from tape was 4 events



Figure 3.3: A single hit displayed by *Pad Monitor*

per second. When replaying zero-suppressed data from disk, the processing rate increased to 15 events per second.

During the analysis process, a program was developed to take the output from the hit-finding pass and create plots of the individual hits. This program, *"Plothits",* allowed for many command-line choices to control the number of plots created, allowing the user to specify cuts on peak height, drift distance, goodness-of-fit, etc. *Plothits* created PostScript files which were then printed.

Figure 3.4 shows typical output from *Plothits* (selecting a single cluster from a representative event). Clearly one can see the gaussian nature of the hit, both in the drift and anode directions. The reader should be aware that the scale is not a constant in fig. 3.4.

Once we were satisfied with the performance of the hit-finder and the



Figure 3.4: Sample output from the *Plothits* visualization program

fitting routines which were used to analyze individual hits, we continued with the analysis.

One of the first plots made during the analysis was an "occupancy plot;" the centroids of all clusters from a given run were plotted as a 2-dimensional histogram in order to assess the illumination of each detector and to check that all instrumented anodes were functioning at some minimum level. Figure 3.5 shows a representative plot, from the first detector in the beam line (SDD # 395). Both axes are in cm, after conversion from drift time and anode position. The drift time has been corrected for the SCA startup delay, as described earlier.

The first observation is the illumination appears not to be even. This is a somewhat erroneous conclusion, however, due to several features of the experiment. The first thing to consider is that only a few anodes were instrumented in each detector. Furthermore, a few anodes in each detector were faulty, and returned either no signal or spurious signals. Thus there are gaps in the active area of the detector which show up in the occupancy plot as regions with a lower hit density. The sharp edges on the illumination region are due to two effects. The lower edge (at drift distance ≈ 0.6 cm) is caused by the SCA dead time, as described earlier. The upper edge (at distance ≈ 2.2 cm) is caused by the fact that only 128 time bins were sampled. The few isolated hits beyond either limit are spurious points from erroneous results from the routines used to fit the charge distribution to obtain a centroid.

The solid lines present in the plot are from hits which contain only one anode. Since it is not possible to do anything with a single data point other than use its anode number to calculate a position, all single-anode clusters on a